

OPTICAL TRANSMISSION METHOD AND OPTICAL TRANSMISSION SYSTEM UTILIZING RAMAN AMPLIFICATION

BACKGROUND OF THE INVENTION

(1) Field of The Invention

The present invention relates to an optical transmission method and an optical transmission system for performing repeating transmission of a wavelength division multiplexed (WDM) signal light while amplifying thereof, and, especially to a superimposition technology of a supervisory signal in a case of amplifying a WDM signal light using Raman amplification.

(2) Related Art

For a WDM optical transmission system for transmitting a WDM signal light including a plurality of optical signals of different wavelengths, there has been known a system structure adopted with an optical amplifying-and-repeating transmission system using an optical amplifier as an optical repeater. For the abovementioned optical amplifier, an erbium doped optical fiber amplifier (EDFA) is generally used, and recently, the use of Raman amplifier together with the EDFA is being greatly reviewed.

A gain of the Raman amplifier has large wavelength dependency, but a gain wavelength characteristic of the Raman amplification can be flattened by the use of a plurality of pumping lights of different oscillation center wavelengths. For example, in the Raman amplifier described in the article, "100nm bandwidth flat gain Raman amplifiers pumped and gain-equalized by 12-wavelength channel WDM high power laser diodes", Y. Emori, et al., OFC' 99, PD19, 1999 and so forth, approximately 100nm as a gain wavelength bandwidth of the Raman amplification is secured by adjusting a pumping light power and its oscillation wavelength.

For the WDM optical transmission system adopted with the optical amplifying-and-repeating transmission system, there is known a technology to supervise and control a plurality of optical transmission apparatuses such as an optical sending terminal, an optical repeater, an optical receiving terminal, and the like, by

superimposing a supervisory signal on a main signal light to be transferred among each of optical transmission apparatus. For one conventional method for superimposing the supervisory signal on the main signal light in this case, there is known a method for modulating a driving current of a pumping light source of the EDFA in accordance with the supervisory signal. Specifically, a transmission speed of the supervisory signal is set to approximately 10Mb/s and its superimposition degree is set to approximately 5% when a transmission speed of the main signal light is set as 10Gb/s.

Considering a case where the above conventional monitor control technology is applied to the WDM optical transmission system constructed by using the optical repeater that uses the EDFA and the Raman amplifier together, which are being reviewed presently, the method for superimposing the supervisory signal on the main signal light is not limited to the method for modulating the pumping light of the EDFA in accordance with the supervisory signal, and a more efficient supervising and controlling technology is expected to be realized. Further, since it can be considered that, in the future, the optical repeater shall be constituted using only the Raman amplifier, it will be useful to realize the supervising and controlling technology capable of coping with the system using such optical repeaters.

SUMMARY OF THE INVENTION

The present invention has been achieved in view of the foregoing problems, and has an object of providing an optical transmission technology using Raman amplification that has realized an efficient supervising and controlling by superimposing a supervisory signal on a main signal light transferred among a plurality of optical transmission apparatuses by making use of a pumping light for Raman amplification.

In order to achieve the above object, an optical transmission method using Raman amplification according to the invention is a method for transmitting a WDM signal light among a plurality of optical transmission apparatuses and supplying a pumping light to a Raman amplification medium existing on an optical transmission path, to Raman amplify the WDM signal light being propagated through the Raman amplification medium, wherein a supervisory signal transferred among the plurality of optical transmission apparatuses is superimposed on the pumping light supplied

to the Raman amplification medium. Moreover, for the abovementioned optical transmission method, when a plurality of pumping lights of different wavelengths are supplied to the Raman amplification medium, the supervisory signal may be superimposed on at least one of the plurality of pumping lights.

According to such an optical transmission method, it is no longer necessary to superimpose the supervisory signal on the entire wavelength band of the WDM signal light as with a case where the pumping light of the conventional EDFA is utilized. Therefore, it becomes possible to superimpose a more efficient supervisory signal in a wavelength band of good excitation efficiency.

Further, in the abovementioned optical transmission method, it is preferable that the pumping light to be superimposed with the supervisory signal is selected out of a plurality of pumping lights based on loss wavelength characteristics of the optical transmission path. Specifically, the pumping light to be superimposed with the supervisory signal can be selected out of the plurality of pumping lights so that a loss of the optical transmission path in a Raman gain band corresponding to a wavelength of the pumping light becomes smaller than the loss of the optical transmission path corresponding to a wavelength of the other pumping light.

Also, in the abovementioned optical transmission method, the construction may be such that a part of the Raman amplified WDM signal light input to the optical transmission apparatus through the optical transmission path is led to an optical filter having a passing band in the Raman gain band corresponding to the wavelength of the pumping light superimposed with the supervisory signal, to detect the supervisory signal using a light passing through the optical filter. According to this method, transmission of the supervisory signal among the respective optical transmission apparatuses can be performed more reliably.

Moreover, in the abovementioned optical transmission method, the construction may be such that the supervisory signal transmitted from a previous stage optical transmission apparatus is detected to superimpose a suppression signal to suppress the detected supervisory signal on the pumping light corresponding to the pumping light superimposed with the supervisory signal from the previous stage optical transmission apparatus, among the pumping lights of different wavelengths to be supplied to the Raman amplification medium. In addition,

the supervisory signal to be sent to a succeeding stage optical transmission apparatus may be superimposed on the pumping light different from the pumping light superimposed with the suppression signal. By applying such a method, it becomes possible to switch a wavelength band where the supervisory signal is superimposed.

The optical transmission method as described above can be applied to an optical transmission system to transmit a WDM signal light using Raman amplification and a Raman amplifier.

The other objects, features and advantages of this invention will become apparent from the following description of embodiment with reference to accompanying drawings.

BRIEF EXPLANATION OF THE DRAWINGS

Fig. 1 is a diagram showing a basic configuration of a Raman amplifier to which an optical transmission method according to the invention is applied.

Fig. 2 is a diagram showing a specific construction example of a pumping light generating section in the Raman amplifier of Fig. 1.

Fig. 3 is a diagram for explaining wavelength locations of a pumping light and a WDM signal light, and a Raman gain band corresponding to each of the pumping light, in the Raman amplifier of Fig. 1.

Fig. 4 is a schematic diagram showing one example of a WDM optical transmission system constructed by applying the Raman amplifier in Fig. 1 to an optical repeater.

Fig. 5 is a diagram showing a specific construction example of an optical repeater to be used for the WDM optical transmission system in Fig. 4.

DETAILED DESCRIPTION OF THE INVENTION

An embodiment according to the present invention will be explained based on drawings as follows.

Fig. 1 is a diagram showing a basic configuration of a Raman amplifier to which an optical transmission method according to the invention is applied.

In Fig. 1, a Raman amplifier 10 comprises a pumping light generating section 11 that generates pumping lights P1~ Pm having different wavelengths, a multiplexer 12 that supplies each of the pumping lights P1~ Pm to a Raman amplification medium 13 existing on an optical transmission path, and a supervisory signal superimposing section 14 that superimposes a supervisory signal on at least one of the pumping lights P1~ Pm to be supplied to the Raman amplification medium 13, and Raman amplifies a WDM signal light (including optical signals S1~ Sn having different wavelengths) being propagated through the Raman amplification medium 13, to output.

A pumping light generating section 11, as shown in Fig. 2, includes pumping light sources (LD) 11A₁~11A_m and driving circuits (DRV) 11B₁~11B_m for generating the pumping lights P1~Pm having different wavelengths and a multiplexer 11C that multiplexes the pumping lights P1~Pm of the respective wavelengths to be output from the respective pumping light sources 11A₁~11A_m, to output. Herein, a supervisory signal from the supervisory signal superimposing section 14 is supplied to the driving circuit 11B_m for driving the pumping light source 11A_m and a driving current generated in the driving circuit 11B_m is modulated in accordance with the supervisory signal, so that the supervisory signal is superimposed on the pumping light P_m generated in the pumping light source 11A_m. The pumping light superimposed with the supervisory signal is not limited to the pumping light P_m, and the supervisory signal can be superimposed on a plurality of pumping lights, and a wavelength of the pumping light superimposed with the supervisory signal can be appropriately selected corresponding to a loss wavelength characteristic of an optical transmission path as described later.

Wavelengths $\lambda_{P1} \sim \lambda_{Pm}$ of the respective pumping lights P1~Pm, for example as shown in a schematic diagram in Fig. 3, are previously set so that a substantially flat Raman gain can be obtained over wavelength bands $\lambda_{S1} \sim \lambda_{Sn}$ of the WDM signal light by combining the plurality of pumping lights P1~Pm based on a wavelength in which respective Raman gains G1~Gm become maximum being positioned at a frequency smaller by 13.2THz than the wavelengths $\lambda_{P1} \sim \lambda_{Pm}$ of the pumping lights. Powers of pumping lights P1~Pm are respectively adjusted as shown in the left side of Fig. 3 taking into consideration the loss wavelength characteristic of the optical transmission path including the Raman amplification medium 13. A setting example

of each pumping light power illustrated in Fig. 3 corresponds to a case where the wavelength bands $\lambda_{S1} \sim \lambda_{Sn}$ of the WDM signal light exhibit characteristics to increase as the loss of the optical transmission path is in the shorter wavelength side, in which the pumping light power on the shorter wavelength side is set to be increased by ΔP compared with the pumping light power on the longer wavelength side. Thereby, a more flattened Raman gain can be realized in regard to the wavelength bands $\lambda_{S1} \sim \lambda_{Sn}$ of the WDM signal light.

The pumping lights $P1 \sim Pm$ of respective wavelengths multiplexed by the multiplexer 11C of the pumping light generating section 11 are supplied to the Raman amplification medium 13 via the multiplexer 12 inserted on the optical transmission path and are propagated in a reverse direction to a transmission direction of the WDM signal light as shown in Fig. 1. The WDM signal light is propagated through the Raman amplification medium 13 to which the pumping lights $P1 \sim Pm$ are supplied, so that optical signals $S1 \sim Sn$ of respective wavelengths are Raman amplified with substantially equal gains. At this time, the supervisory signal superimposed on the pumping light Pm is superimposed only on the optical signal on the long wavelength side in the vicinity of the wavelength λ_{Sn} to be superimposed mainly in accordance with the Raman gain Gm corresponding to the pumping light wavelength λ_{Pm} . Thus, the WDM signal light is transmitted among the optical transmission apparatuses constructing the optical transmission system, while being Raman amplified, thereby performing transmission of the supervisory signal simultaneously.

Fig. 4 is a schematic diagram showing one example of a WDM optical transmission system constructed by applying the Raman amplifier 10 in Fig. 1 to an optical repeater or the like.

In the WDM optical transmission system in Fig. 4, a WDM signal light including optical signals $S1, S2, \dots, Sn$ is transmitted via an optical transmission path 400 from an optical sending terminal 200 to an optical receiving terminal 300. On the optical transmission path 400, optical repeaters 100 equipped with the Raman amplifier 10 in Fig. 1 are positioned in required repeating intervals, and the WDM signal light to be transmitted on the optical transmission path 400 is repeatedly transmitted while being Raman amplified. Here, the optical sending terminal 200, each of the optical repeaters 100, and the optical receiving terminal 300 correspond

to a plurality of optical transmission apparatuses constructing an optical transmission system.

The optical sending terminal 200 includes n pieces of optical senders (E/O) 201 for generating the optical signals S_1, S_2, \dots, S_n , a multiplexer 202 for multiplexing the optical signals S_1, S_2, \dots, S_n output from the respective optical senders 201 to output, a post-amplifier 203 for amplifying the WDM signal light output from the multiplexer 202 to a required level, and a SV sending section 204 for superimposing a supervisory signal on a main signal light via the post-amplifier 203. For the above post-amplifier 203, the supervisory signal from the SV sending section 204 may be superimposed on a pumping light for Raman amplification by applying the Raman amplifier 10 shown in Fig. 1 as described above, or alternatively, the supervisory signal from the SV sending section 204 may be superimposed on a pumping light of the EDFA by applying the EDFA as with the conventional technique.

Each optical repeater 100, as shown in Fig. 5, amplifies the WDM signal light sent via the optical transmission path 400 to a required level by making use of a known EDFA 101 together with the Raman amplifier 10 having the basic configuration shown in Fig. 1 as described above. Specifically, the Raman amplifier 10 is arranged on a front stage of the EDFA 101 to further amplify the Raman amplified WDM signal light by the EDFA 101. Here, an optical coupler 102, an optical filter 103, and a supervisory signal detecting section 104 are disposed within each optical repeater 100 in order to detect the supervisory signal superimposed on the main signal light in the optical sending terminal 200 or the preceding stage optical repeater 100.

The optical coupler 102 is inserted, for example, between an input terminal of the optical repeater 100 and the Raman amplification medium 13, and branches a part of the WDM signal light input from the optical transmission path 400 to the optical repeater 100 to output it to the optical filter 103. The optical filter 103 extracts a wavelength light component equivalent to a Raman gain band corresponding to a wavelength of the pumping light superimposed with the supervisory signal (pumping light P_m in the setting examples in Fig. 2 and Fig. 3), to output it to the supervisory signal detecting section 104. The supervisory signal detecting section 104 converts an optical signal extracted at the optical filter 103 into an electrical signal with a light receiving element not shown herein, to detect a supervisory signal superimposed on

the electrical signal. The supervisory signal detected at the supervisory signal detecting section 104 is utilized in a supervisory control for the optical repeater and also is transmitted to the supervisory signal superimposing section 14.

The construction using the EDFA 101 together with the Raman amplifier 10 has been described as the optical repeater 100. However, for the optical transmission apparatus using the optical transmission system according to the invention, it is also possible to amplify a signal light utilizing only the Raman amplifier 10.

The optical receiving terminal 300 includes a preamplifier 301 for receiving the WDM signal light sent from the optical transmission path 400 to amplify it to a required level, a demultiplexer 302 for demultiplexing the WDM signal light amplified at the preamplifier 301 to the optical signals S1~Sn of respective wavelengths to output it, n pieces of optical receivers (O/E) 303 for performing a receiving process of each optical signal S1~Sn output from the demultiplexer 302, an optical coupler 304 for branching a part of the WDM signal light sent to the demultiplexer 302 from the preamplifier 301, and a SV receiving section 305 for detecting a supervisory signal superimposed on the WDM signal light by using a branch light of the optical coupler 304. The preamplifier 301, the demultiplexer 302, and the each optical receiver 303 are the same as those used in the conventional optical receiving terminal. The optical coupler 304 corresponds to the optical coupler 102 disposed in the optical repeater 100, and the SV receiving section 305 includes a function corresponding to the optical filter 103 and the supervisory signal detecting section 104 disposed in the optical repeater 100.

In the WDM optical transmission system of the abovementioned construction, optical signals S1~Sn of respective wavelengths generated at respective optical senders 201 of the optical sending terminal 200 are wavelength division multiplexed at the multiplexer 202, to be sent to the post-amplifier 203. In the post-amplifier, the WDM signal light from the multiplexer 202 is amplified, and the supervisory signal from the SV sender 204 is superimposed on the pumping light, thereby generating the WDM signal light including the supervisory signal, to be sent to the optical transmission path 400.

When the WDM signal light sent to the optical transmission path 400 reaches the optical repeater 100, it is sent to the Raman amplifier 10 and also a part thereof is branched at the optical coupler 102 to be sent to the optical filter 103. In the optical filter 103, a wavelength optical component superimposed with the supervisory signal at the optical sending terminal 200 is extracted. A light having passed through the optical filter 103 is sent to the supervisory signal detecting section 104 at which the detection process is performed for the supervisory signal from the optical sending terminal 200. Then, an operation of the optical repeater 100 is controlled based on the detection result of the supervisory signal detecting section 104.

The wavelength light including the supervisory signal is extracted by using the optical filter 103, so that the detection of the supervisory signal is performed with higher accuracy. Namely, the wavelength optical component superimposed with the supervisory signal is at a wavelength band of a part of the WDM signal light in the superimposition of the supervisory signal using the pumping light for Raman amplification. Therefore, when a branch light of the optical coupler 102 is used for the detection process of the supervisory signal without using the optical filter 103, the wavelength light on which the supervisory signal is not superimposed becomes a noise component, causing deterioration of SN ratio in supervisory signal detection. Accordingly, only the wavelength including the supervisory signal is extracted by using the optical filter 103, thereby enabling the detection of the supervisory signal by a monitoring light with a good SN ratio.

The WDM signal light sent to the Raman amplifier 10 after having passed through the optical coupler 102 is Raman amplified by being propagated through the Raman amplification medium 13 to which the pumping lights $P_1 \sim P_m$ are supplied. At this time, the supervisory signal generated at the supervisory signal superimposing section 14 has been superimposed on the pumping light P_m among the pumping lights $P_1 \sim P_m$, and the above supervisory signal is superimposed on the WDM signal light of the wavelength band corresponding to the Raman gain band corresponding to this pumping light P_m . The supervisory signal generated at the supervisory signal superimposing section 14 is a signal suppressing a supervisory signal component from the optical sending terminal 200 detected at the supervisory signal detecting section 104, and indicating monitor information to be transmitted to the next optical repeater 100.

It is preferable that the wavelength band of the WDM signal light to be superimposed with the supervisory signal is in advance designed to be in the wavelength band where a loss of the optical transmission path including the Raman amplification medium 13 becomes relatively small. With this design, superimposition of the supervisory signal on the main signal light can be performed more efficiently. Namely, in order to superimpose the supervisory signal on the signal light of a wavelength band where the loss of the optical transmission path is relatively large, it is required to perform the superimposition of a relatively large amplitude on the pumping light corresponding to this wavelength band, resulting in a possibility that an operation of the pumping light source becomes strict to the maximum output standard. To avoid this problem, the supervisory signal is superimposed on the signal light of a wavelength band where the loss of the optical transmission path is relatively small, so that it becomes possible to make the power and amplitude of the pumping light small, thereby enabling to easily operate the pumping light source with respect to the maximum output standard. Explaining a specific example, if considering a case where the WDM signal light of 1.55 μ m band (C band), the supervisory signal may be superimposed on the pumping light having a Raman gain band on the wavelength side with a relatively small loss of the optical transmission path by avoiding a short wavelength band in the vicinity of 1.4 μ m where the loss of the optical fiber transmission path becomes large due to an influence of an OH group. It is necessary to pay an attention to the modulation efficiency reduction resulting from the amplification of the pumping light on the long wavelength side by the pumping light on the short wavelength side (pump to pump), when selecting the pumping light to be superimposed with the supervisory signal.

Here, the supervisory signal transmitted from the previous stage apparatus is suppressed, and the supervisory signal indicating the supervisory information to be sent to the succeeding stage apparatus is generated at the supervisory signal superimposing section 14, so that the supervisory signal is superimposed on the pumping light (Pm) of the same wavelength. However, the present invention is not limited thereto. It is possible to switch the pumping light to be superimposed with the supervisory signal between neighboring apparatuses. Specifically, the suppression signal suppressing (offsetting) the supervisory signal is superimposed on the pumping light superimposed with the supervisory signal at the preceding apparatus and the supervisory signal to be sent to the succeeding stage apparatus is

superimposed on the pumping light different from the pumping light superimposed with the suppression signal.

The WDM signal light amplified as above at the amplifier 10 of the previous stage of the optical repeater 100 is sent and further amplified at the succeeding stage EDFA 101, and thereafter, output to the optical transmission path 400. Then, the WDM signal light amplified and repeatedly transmitted sequentially at each optical repeater 100 as with the above, reaches the optical receiving terminal 300, and thereafter, sent to the preamplifier 301 to be amplified to a required level. The WDM signal light amplified at the preamplifier 301 is sent to the demultiplexer 302 to be demultiplexed to respective optical signals $S1 \sim Sn$, and also a part thereof is branched at the optical coupler 304 to be sent to the SV receiving section 305.

At the SV receiving section 305, the wavelength light component superimposed with the supervisory signal is extracted by using the optical filter from a branched light of the optical coupler 304, and the detection process is performed for the supervisory signal from the previous stage optical repeater 100 using the extracted wavelength light. An operation of the optical receiving terminal 300 is controlled by utilizing the detection result of the SV receiving section 305.

In this manner, according to the present WDM optical transmission system, the supervisory signal can be transferred among the optical transmission apparatuses by superimposing the supervisory signal on the pumping light for Raman amplification and it becomes unnecessary to superimpose the supervisory signal on the entire wavelength band of the WDM signal light, differently from the system using the pumping light of the conventional EDFA. As a result, it becomes possible to perform the good efficient superimposition of the supervisory signal at a wavelength band having good excitation efficiency. Moreover, the detection process is performed for the supervisory signal by extracting only the wavelength light including the supervisory signal by using the optical filter, thereby enabling transmission of the supervisory signal among the optical transmission apparatuses more reliably. Such a transmission technology of the supervisory signal can easily cope with a case where a system performing an optical amplification using only the Raman amplifier will be realized, and thus is useful.

In the embodiment as described above, for the Raman amplifier 10, there has been described the construction where the Raman amplification medium is supplied with a plurality of pumping lights having different wavelengths, but the present invention is not limited thereto. The present invention can be also applied to the construction where the Raman amplification medium is supplied with the pumping light having a single wavelength. In Fig. 5, there has been shown a so-called centralized Raman amplification type construction in which the Raman amplification medium 13 is positioned within the optical repeater 100, but a so-called distributed Raman amplification type construction is made possible in which the optical transmission path 400 connected to the optical repeater 100 is used as the Raman amplification medium.

100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000